



# Interior Zone Protectors SAS10T2V2, SAS8T2V2, SAS7T1V1, SAS7T1, and SAS7/8

## Features and Benefits

- UL listed surge protection
- Rated for 120VAC grounded outlets
- Installation by homeowner for multiple appliances
- Visual indication of “Protected” and “Grounded” status
- Lifetime product warranty
- Lifetime \$100,000 connected equipment warranty when all 3 surgeassure™ Main Zone Protectors are installed

The surgeassure™ SAS10T2V2, SAS8T2V2, SAS7T1V1, SAS7T1, and SAS7/8 are specially designed for Home Theater and Home Office applications.

The SAS10T2V2 provides protection for 10 AC outlets with space for 4 adapter plugs, 2 coax lines and 2 telephone/fax/modem lines.

The SAS8T2V2 provides protection for 8 AC outlets with space for 4 adapter plugs, 2 coax lines and 2 telephone/fax/modem lines.

The SAS7T1V1 provides protection for 7 AC outlets with space for 2 adapter plugs, 1 coax line and 1 telephone/fax/modem line.

surgeassure™

14550 58th Street North Clearwater, Florida 33760  
1.800.727.0669 - info@surgeassure.com - www.surgeassure.com



The SAS7T1 provides protection for 7 AC outlets with space for 2 adapter plugs and 1 telephone/fax/modem line.

The SAS7/8 provides protection for 7/8 AC outlets with space for 2 adaptor plugs.

All of the surge protectors can be securely mounted using the slots provided on the back of the unit.

Major household electrical and electronic equipment are covered against surge damage for Lifetime during ownership by the original purchaser when a SAS10T2V2, SAS8T2V2, SAS7T1V1, SAS7T1, or SAS7/8 is installed and when surgeassure™ Main Zone Protectors are installed.

If the SAS10T2V2, SAS8T2V2, SAS7T1V1, SAS7T1 or SAS7/8 surge protector is damaged during the warranty period, surgeassure™ will replace it free of charge!

# Technical Specifications

AC Surge Protection	SAS10T2V2	SAS8T2V2	SAS7T1V1	SAS7T1	SAS7/8
Surge Capacity	240,000 A	240,000 A	168,000 A	75,000 A	168,000 A
Line Voltage	120VAC	120VAC	120VAC	120VAC	120VAC
EM/RFI Filtering	Yes	Yes	Yes	Yes	Yes
Protected AC Outlets	10	8	7	7	7/8
Protected Coax Lines	2	2	1	N/A	N/A
Protected Phone Lines	2	2	1	1	N/A
Coax Patch Cord Provided	Yes	Yes	Yes	N/A	N/A
Phone Patch Cord Provided	Yes	Yes	Yes	Yes	N/A

Agency Approvals & Warranty	
UL Listings	1283 Filter, 1449 TVSS
UL 1449 Rating	330V
Product Warranty	Lifetime
*Connected Equipment Warranty	Lifetime

\*Requires all 3 surgeassure™ Main Zone Protectors to be installed at the homes incoming service.



TE/1C40 Main Zone Protector

## Selection Information

### Plug Strip Interior Zone Protectors

Catalog Number	Description
SAS10T2V2	10 AC Outlets, 2 Coax Lines, 2 Telephone/fax/modem Line
SAS8T2V2	8 AC Outlets, 2 Coax Lines, 2 Telephone/fax/modem Line
SAS7T1V1	7 AC Outlets, 1 Coax Lines, 1 Telephone/fax/modem Line
SAS7T1	7 AC Outlets, 1 Telephone/fax/modem Line
SAS7/8	7/8 AC Outlets

For More Information Contact:

### Installation:

1. If the surgeassure™ protector is equipped with telephone protection, use the supplied telephone cord to connect the telephone line from the input jack of the protector to the wall jack.
2. Connect the telephone equipment to the output jack of the protector using the existing telephone cord.
3. Connect the AC cords of the equipment to be protected to the surgeassure™ protector.
4. Connect AC power cord of the protector to a wall outlet.
5. Turn on the surgeassure™ protector using the on/off switch.
6. The indicator lights should be on after the protector has been installed.
7. If the protector has coax cable protection, connect cable from signal source to the input jack of the protector and cable from the output jack of the protector to the TV or other protected equipment.

surgeassure™

14550 58th Street North Clearwater, Florida 33760  
1.800.727.0669 - info@surgeassure.com - www.surgeassure.com